

TPCC MANUAL

ENGLISH VERSION



PSI
Technics



000500999000



**TECHNICAL
DOCUMENTATION**

**Thermo Protection
Cooling Case**

MODELS

**TPCC/DM
TPCC/T/DM
TPCC/CLV
TPCC/LMS**



Company Headquarters

PSI Technics GmbH
An der Steinkaul 6a
D-56333 Winningen, Germany
Phone +49 2630 91590 - 0
Fax +49 2630 91590 - 99
info@psi-technics.com
www.psi-technics.com/EN/

Copyright and Trademarks

Copyright © 2007-2023 , PSI Technics GmbH All rights reserved.
All trademarks are the property of their respective owners.

Release Notice

This is the November 2023 release (Version 3.4.8) of the TPCC User Manual. It applies to the TPCC/DM, T/DM, CLV and LMS models of PSI Technics' Thermo Protection Cooling Case (TPCC). The following limited warranties give you specific legal rights. You may have others, which vary from state/jurisdiction to state/jurisdiction. Hardware Limited Warranty: PSI Technics warrants that this TPCC hardware product (the 'Product') shall be free from defects in materials and workmanship and will substantially conform to PSI Technics' applicable published product specifications for a period of one (1) year, starting from the date of purchase. This limited warranty does not apply to software or firmware products.

Warranty Remedies

PSI Technics' sole liability and your exclusive remedy under the warranties set forth above shall be, at PSI Technics' option, to repair or replace any Product that fails to conform to such warranty ('Nonconforming Product'), or refund the purchase price paid by you for any such Nonconforming Product, upon your return of any Nonconforming Product to PSI Technics, together with a copy of the original proof of purchase, a full description of the application the product is used for as well as a description of the problem. The product must be packaged for safe transportation.



Warranty Exclusions and Disclaimer

These warranties shall apply only in the event and to the extent that: (i) the Product is properly and correctly installed, configured, interfaced, stored, handled, operated, serviced and maintained in accordance with PSI Technics' relevant user manual(s) and product specifications, and; (ii) the Product is not modified or misused. The preceding warranties shall not apply to, and PSI Technics shall not be responsible for: defects or performance problems resulting from (i) the combination or utilization of the Product with products, information, data, systems or devices not made, supplied or specified by PSI Technics; (ii) the operation of the Product under any specification other than, or in addition to, PSI Technics' standard specifications for its products; (iii) the unauthorized modification or use of the Product; (iv) the removal of the product's serial numbers or the altering, defacing or removal of any other markings or parts of the Product; (v) damage caused by accident, lightning or other electrical discharge, excessive current/voltage or temperature, fresh or salt water immersion or spray; or (vi) normal wear and tear on consumable parts (e.g., batteries). PSI Technics GmbH does not warrant and cannot be held liable for the results resulting from the use of this product. The warranties above state the entire liability of PSI Technics GmbH and your exclusive remedies relating to the performance of the product. Except as otherwise expressly provided herein, the product and accompanying documentation and materials are provided AS-IS and without express or implied warranties of any kind by either PSI Technics or anyone who has been involved in its creation, production, installation or distribution, including but not limited to, the implied warranties of merchantability and fitness for a particular purpose, title and non-infringement. The stated express warranties are in lieu of all obligations or liabilities on the part of PSI Technics arising out of, or in connection with, any products or software. Some states and jurisdictions do not allow limitations on duration or the exclusion of an implied warranty, so the above limitation may not apply to you.

Limitation of Liability

The entire liability of PSI Technics GmbH under any provision herein shall be limited to the amount that was paid by you for the product. To the maximum extent permitted by applicable law, in no event shall PSI Technics GmbH or its suppliers be liable for any indirect, special, incidental or consequential damages whatsoever, under any circumstances or legal theory relating in any way to the use, quality or performance of products, software and accompanying documentation and materials, (including, without limitation, damages for loss of business profits, business interruption, loss of business information, or any other pecuniary loss, and any claims of third parties), regardless of whether PSI Technics has been advised of any such loss and regardless of the course of dealings which develops between you and PSI Technics. Because some states and jurisdictions do not allow the exclusion or limitation of liability for consequential or incidental damages, the above limitation may not apply to you. Regardless of the above, if you purchased this product in the European Union, the aforementioned warranty provisions may not apply to you. Please contact PSI Technics GmbH to obtain applicable warranty information.

Changes and Revisions

Table 1: Changes and Revisions

Ver.	Date	Changes
1.09	23.02.2011	Modification
1.10	09.05.2012	Modification
2.00	30.07.2012	Release V2.0
2.01	28.08.2012	Modification
2.02	28.12.2012	Modification
2.03	10.05.2013	Modification
2.04	29.06.2013	Update Cable Feed
3.00	11.12.2013	Release V3.0
3.20	06.11.2014	Update Circuit Board
3.4	04.10.2017	Modification
3.4.4	18.12.2018	Update Error Monitoring
3.4.5	02.03.2020	Update Environmental Specifications
3.4.6	25.09.2020	Replaced circuit diagram page 22
3.4.7	25.03.2021	Modification
3.4.8	15.11.2023	Update Error Outputs

Preface

Welcome to PSI Technics

Thank you for choosing the PSI Technics Thermo Protection Cooling Case (TPCC). The TPCC Professional is a thermal protection system specifically designed for protecting sensors that are used in high-temperature environments. It was designed for use with a variety of sensors that are used in industrial applications, such as laser distance meters and data light barriers. The TPCC is made of state-of-the-art materials and equipped with temperature controls. It is an extremely powerful system, based on state-of-the-art technology with thermoelectric components.

Industrial environments are often subject to very harsh conditions, such as dust, humidity or extreme temperatures. These conditions, however, are rarely considered during the development of sensors and structural components. Excessive temperatures can cause electronic components and sensors to malfunction. Most often, these components and sensors play a critical role in production processes and failures or malfunctions can result in extremely costly outages.

PSI Technics addressed this problem by developing the TPCC product family. The TPCC product range comprises powerful solutions that prevent temperature-induced sensor failures.

Table of Contents

Changes and Revisions	IV
Preface	V
Contents	VI
1 Introduction	1
1.1 Overview	1
2 TPCC Professional	2
2.1 General Description	2
2.1.1 Package Contents	4
2.1.2 Product Specifications	6
2.1.3 TPCC Front	7
2.1.4 Top View	11
2.1.5 Back	12
2.1.6 TPCC Dimensions	13
2.2 Safety	15
2.2.1 Safety Overview	15
2.2.2 Cabling	15
2.2.3 Transport	15
2.2.4 TPCC Glass Pane	16
2.2.5 Environmental Specifications	16
2.2.6 Power Supply	16
2.2.7 Electromagnetic Interference (EMI)	16
2.2.8 Maintenance	17
2.3 Mechanical Installation and Alignment	18
2.3.1 Mounting the TPCC Using Threaded Holes	18
2.3.2 Mounting the TPCC Using Clearance Holes	19
2.3.3 Installing the Upper Housing	20
2.3.4 Aligning the TPCC for Use with Optical Sensors	20

2.4	Wiring	21
2.4.1	Cables	23
2.4.2	Power Supply	23
2.4.3	Cable Connections	23
2.4.4	Cable Feeds	24
2.4.5	Connecting the Cables	26
2.4.6	Pin Allocation	27
2.4.7	Error Monitoring (optional)	28
2.4.8	Connecting the Solid-state Relay	29
2.4.9	Installing the Solid-state Relay	30
2.5	Operating the TPCC	31
2.5.1	SICK DME3000/4000/5000 Distance Meters	32
2.5.2	SICK DS/DT500 Distance Meters	32
2.5.3	SICK DMT-DML Distance Meters	32
2.5.4	SICK DL100 Pro Distance Meters	32
2.5.5	SICK CLV631/690 Bar Code Scanners	32
2.5.6	SICK LMS400 Distance Meters	32
2.5.7	SICK WL12G Reflex Sensor	33
2.5.8	SICK Lector [®] 620 Professional / ICR620 Bar Code Reader	33
2.5.9	SICK DL/DT20	33
2.5.10	SICK Dx1000	33
2.6	Troubleshooting	34
2.6.1	Troubleshooting the TPCC	34
2.7	Cable Length	35
2.7.1	Cable Cross-Section $1.5mm^2$	35
2.7.2	Cable Cross-Section $2.5mm^2$	36
2.8	Recommended Connectors	37
3	Reader Comment Form	40
4	Notes	42

5 Support	43
5.1 General	43
5.2 Service and Support	43
6 List of Figures, List of Tables and Appendix	44
List of Figures	45
List of Tables	47
A Appendix	48
A.1 Appendix - Mounting Instructions (Adapter Plate)	48

1 Introduction

This user manual describes different models of PSI Technics' "Thermo Protection Cooling Case" with thermostatic control. Although a variety of sensors can be used with the TPCC, this manual focuses on the use of SICK DMT-DML, DME3000/4000/5000 DL100 Pro, Dx1000, DS/DT500, WL12G, Lector® 620/ICR620, CLV631/CLV609, LMS400 and DL/DT20 sensors.

1.1 Overview

This technical documentation is an important tool for installing and using PSI Technics' TPCC Professional System. It is designed for technically trained staff and is aimed at facilitating the installation and use of the system.



Warning - A warning indicates situations that could lead to potential damage. Read this information carefully to prevent damage, errors or malfunctions.

Prior to installing and using the TPCC, PSI Technics recommends analyzing the environmental conditions at the operating site. To support this process, PSI Technics offers a thermal imaging spot analysis using a thermal imaging camera as well as a long-term temperature analysis that lasts over a period of several days.



NOTE - Inspect each shipment immediately upon receipt and report any damages to PSI Technics.

2 TPCC Professional

2.1 General Description

The TPCC Professional System consists of the Thermo Protection Cooling Case. It extends the sensors' application range to an environmental temperature of 176°F (+80°C).

The sensor is mounted on adapter plates that are specific to the sensor (as shown in the Appendix, Figures 25-36) and must be installed inside the TPCC Professional housing. The compact form of the TPCC allows for easy installation on site. When the TPCC is operated within the admissible ambient temperature range, the sensor will be kept at a permissible operating temperature at all times.

Different models of the TPCC Professional System are available (see Table 2). The appropriate version depends on the type of sensor you are using.

The TPCC/T/DM model is used for SICK DMT/DML distance meters. The differentiating feature of the 'T' model is the front pane that is mounted inside the tube and is tilted along the beam axis. This construction ensures a smooth operation of SICK DMT/DML sensors. The bottom of the tube has a small outlet hole that allows condensation to escape. The tube is integrated into the upper part of the 'T' model housing.

Table 2 below contains an overview of the TPCC models that can be used for the different sensors described in this manual. The glass panel for the sensor assembly is located either at the front or at the top of the corresponding TPCC model housing.

Table 2: Overview of Sensors and Corresponding TPCC Models

Sensor	DM	T/DM	CLV	LMS
SICK DMT-DML	X	X		
SICK DME3000 / DME4000/DME5000	X			
SICK DL100 Pro	X			
SICK Dx1000	X			
SICK DS/DT500	X			
SICK WLG12	X			
SICK Lector [®] 620 Professional / ICR 620	X			
SICK CLV631/CLV690			X	
SICK LMS400				X
SICK DL/DT20	X			

2.1.1 Package Contents

The TPCC includes the following standard components:

- Lower housing with cooling unit
- Sensor-specific upper housing
- Adapter plate for mounting the sensor
- Sensor mounting screws for adapter plate
- Solid state relay (SSR) for wear-free cooling control
- Dessicant bag
- Different types of cable feeds (4 types)
 - 1 40 x 40 mm cable feed with large feed-through
 - 2 20 x 20 mm cable feeds with large feed-through
 - 1 20 x 20 mm cable feed with small feed-through
 - 3 20 x 20 mm cable feeds without feed-through



NOTE - Please note that the mounting screws for installing the TPCC in the customer's facility are NOT part of the delivery, since the mounting screws depend on the installation and may vary. However, the TPCC can generally be mounted on the clamping and alignment bracket using three M10 screws (see Figure 9 in section 2.3).

In addition, the following components can be ordered for a particular sensor:

- 24VDC/20 power supply
- Circuit breaker
- TPCC cable (YSLYCY 7 x 1.5 mm²)
- Sensor cable
- Sensor connectors
- Installation kit
(includes all required components for operating the TPCC)
 - Power supply
 - Fuse
 - Terminal board
 - Single-core cable
 - Grounding bar with mount
 - Shielding terminal



NOTE - If a particular item that you would like to order is not listed in the specifications section or on the fax order form, please send an email to info@psi-technics.com, we will provide the corresponding order details.

2.1.2 Product Specifications

TPCC Specifications: The protective case for industrial use is made of lightweight material (Polyamide-6) that provides excellent damping and insulation properties. The TPCC provides:

- Easy installation and alignment of the Y/Z axes
- 24V power supply (PELV)
- Automatic deactivation at excessive temperatures (over-temperature shutdown)
- Operating temperature range: -40°F to 176°F (-40°C to +80°C)
- SKINTOP[®] CUBE Screw-type terminal block cable feeds
- Designed for industrial applications
- Thermostatic Control
- Weight: 15.43 lbs (7 kg) without adapter plates
- IP protection: IP54 when mounted vertically, IP55 when mounted horizontally
- Protection class: 3 (PELV, Protective Extra Low Voltage)

Available as an option:

- Error message in case of over-temperature shutdown, isolated switching contact
- Error message when one or both fans are failing, isolated switching contact

2.1.3 TPCC Front

The main feature at the front of the TPCC/DM is the centered protective glass panel (or the tube mounted in the TPCC/T/DM). The TPCC/CLV, and TPCC/LMS models have a closed front and the glass panel is located at the top of the TPCC housing. The protective glass panel is the opening the sensor uses for data collection and for calculating distances or reading data. The glass panel should be cleaned on a regular basis to avoid measurement errors or error messages. In addition, the sensor's working range must be taken into account when mounting the TPCC.



NOTE - Inspect each shipment immediately upon receipt and report any damages to PSI Technics.



Warning - During transport, the glass panel of the TPCC/DM, TPCC/CLV and TPCC/LMS models is protected by a cover. This cover must be removed prior to installing the TPCC Professional System. The TPCC/T/DM version does not require a separate protective cover as the housing design provides adequate protection for the glass panel during transport. The air supply holes shown in Figure 5 and the air vent holes shown in Figures 1, 2 and 4 must be kept clean and free of obstructions at all times during operation.



Warning - During operation, a laser beam is emitted through the glass panel. To prevent potential eye injuries, never look directly at the glass panel or through it while the device is running.




Figure 1: TPCC/DM Front




Figure 2: TPCC/T/DM Front




Figure 3: TPCC/CLV & TPCC/LMS Front

2.1.4 Top View




Figure 4: TPCC/CLV & TPCC/LMS Top View

2.1.5 Back




Figure 5: TPCC Back - All Models

The SKINTOP[®] CUBE screw-type terminal block cable feeds that supply power to the TPCC and the enclosed sensor are located at the back of the TPCC housing. The SKINTOP[®] CUBE cable feed system can be customized depending on the number of required cable feeds. Unused terminal blocks must be protected with a blind cap (see Section 2.4.4). The air vent and air supply holes are located underneath the terminal blocks.



Warning - The air vent and air supply holes must be kept clean and free of obstructions. Do not place any objects inside these holes.

2.1.6 TPCC Dimensions




Figure 6: TPCC Back View - All Models




Figure 7: TPCC/DM and CLV Models - Side View




Figure 8: TPCC/T/DM with Tube - Side View

An aperture ('A') in the TPCC/T/DM model with a diameter of 5 mm at the bottom of the tube in front of the glass pane permits condensation to escape, as shown in Figure 8.



Warning - Aperture ('A') should be checked on a regular basis and kept free of obstructions.

2.2 Safety

2.2.1 Safety Overview



Warning - For your own safety, please read the following warnings carefully before using the system. Always keep this manual at hand for easy reference. To prevent personal injuries and property damage, strictly follow all instructions and procedures described in this manual. The system is an electromechanical device and may malfunction. To prevent potential malfunctions, appropriate safety measures must be taken prior to installing and operating the TPCC. This is especially important for systems that are critical for production.



Warning - The internal components are sensitive to static electricity. Never modify, disassemble or repair the system yourself. All modifications must be performed by authorized service personnel.



Warning - The system must be correctly installed, mounted and connected prior to initial operation.

2.2.2 Cabling



Warning - Always turn off the TPCC before connecting or removing any feeds or cables to avoid potential damage.

2.2.3 Transport



Warning - Only transport the TPCC inside the specially designed cover. Use the sturdy cardboard cover to transport the TPCC. Proper packaging ensures that the TPCC is protected from damage during transport.

2.2.4 TPCC Glass Pane



Warning - All TPCC models (except the TPCC/T/DM) have a protective film on both sides of the glass pane. Remove the protective films prior to operating the TPCC. The glass pane of the TPCC/T/DM does not require a protective film as the integrated tube provides sufficient protection.

2.2.5 Environmental Specifications

- Operating temperature: -40°F to 167°F (-40°C to +75°C)
(Up to 176°F (+80°C) for about 1 hour)
- Storage temperature: -40°F to 122°F (-40°C to +50°C)



Warning - Ensure that the mounted sensor/device match the environmental specifications of the application case to avoid failures.

2.2.6 Power Supply

- Rated voltage: 24 VDC - 30 VDC
- Start-up current: 15 A maximum @ 24 VDC
- Operating current: 11 A maximum @ 24 VDC

2.2.7 Electromagnetic Interference (EMI)

Electric Welding



Warning - Electric welding creates an electromagnetic field. This electromagnetic field induces a strong electromagnetic noise. Remove all TPCC feeds and cable connections prior to performing electric welding close to the device.



Warning - Always disconnect the power supply prior to performing any welding on the housing.

2.2.8 Maintenance

Depending on the operating conditions of the TPCC Professional, the TPCC's cooling element should be inspected and cleaned every six months. A cooling element that is clogged with dirt can obstruct the airflow and affect the TPCC's cooling performance. Use canned compressed air with a small air nozzle that can be inserted via the fan vent holes to clean the cooling element. This also ensures that the fans are protected against over-revving that could be caused by a compressed air blast.



Warning - Disconnect the TPCC from the power supply prior to performing maintenance on the housing.



Warning - Ensure that the fans are working properly after the cooling element has been cleaned.

2.3 Mechanical Installation and Alignment

2.3.1 Mounting the TPCC Using Threaded Holes

1. The clamping and alignment bracket is already attached to the TPCC. To mount the TPCC with the alignment bracket, drill 3 holes into the mounting surface (diameter (\varnothing) 8.5 mm) to hold the clamping and alignment bracket (shown in Figure 9).
2. Tap the three drill holes (M10).
3. Insert screws, washers and spring rings (not included) and lightly tighten the screws, as shown in Figure 9.
4. Align the TPCC.
5. After aligning the TPCC, securely tighten the screws with a torque wrench.




Figure 9: Mounting the TPCC

2.3.2 Mounting the TPCC Using Clearance Holes

1. The clamping and alignment bracket is already attached to the TPCC. To mount the TPCC with the alignment bracket, drill 3 holes into the mounting surface (\varnothing 10.5 mm) to hold the clamping and alignment bracket (shown in Figure 9).
2. Insert and lightly tighten the screws (1), washers (4), spring rings (5) and nuts (6), as shown in Figure 10 (2=Mounting area, 3=Clamping and alignment bracket). Please note that the mounting components are not included and must be ordered separately.
3. Align the TPCC.
4. After aligning the TPCC, securely tighten the screws with a torque wrench.




Figure 10: Mounting the TPCC Using Clearance Holes

2.3.3 Installing the Upper Housing

After mounting the sensor inside the TPCC according to the mounting instructions provided in Appendix A, the TPCC's upper housing must be mounted on the lower housing. The screws of the upper housing must first be hand-tightened and then tightened with a torque of $1Nm$ using a torque wrench to ensure the dust and water protection.



Warning - The TPCC is only protected to IP55 when mounted horizontally. If the TPCC needs to be mounted in a different position the protection reduces to IP54.

2.3.4 Aligning the TPCC for Use with Optical Sensors

Mount the TPCC so that the sensor beam always hits the center of the object or reflector, regardless of the distance from the TPCC. For additional information on aligning the sensor, please refer to the corresponding documentation of the sensor manufacturer.

2.4 Wiring

General

All cables leading from the TPCC Professional system to the temperature controls must be installed safely and securely. Only cables that are appropriate for use with the TPCC Professional system should be connected to the device.



Warning - The existing board has been replaced with a new version (Rev. 2). The schematics and wiring information on the following pages refer to this new board. It will be shipped as a default board with all TPCC models starting **August 2014**.

The old and new board versions are shown in the pictures below. For TPCC models that were ordered prior to August 2014 and include an old board version, please use the wiring schematic for the old board in the manual version that was included in your shipment.



Figure 11: New Board




Figure 12: Old Board

Figure 13 contains a schematic representation of the TPCC Professional wiring.




Figure 13: TPCC Professional Wiring

2.4.1 Cables

2.4.2 Power Supply

Feed the power supply cable through the cable screw located at the bottom of the back housing.

- Recommended cable: YSLYCY 7 x 1.5 mm²

Ensure that the +24 VDC feed has the right polarity to avoid damaging the components. Cable length is limited to 82 ft (25 m).

2.4.3 Cable Connections

1. To connect the cables, remove the top of the TPCC housing.
2. Feed the cables through the screw-type cable feed connections and connect them to the terminal block. For additional information, please refer to sections 2.4.4, 2.4.5, 2.4.6 and 2.4.8 in this manual.

2.4.4 Cable Feeds




Figure 14: Cable Feeds at the Back of the TPCC Housing

The TPCC models have a modular SKINTOP[®] CUBE cable feed. The 40x40mm gasket must be used for the power supply cable feed. Several gasket inserts for the sensor cable feeds are included in the delivery. Unused feeds must be protected with corresponding blind caps to ensure the dust and water protection.




Figure 15: Cable Feeds and Frame Installation Overview

SKINTOP[®] CUBE screw-type terminal block cable feeds consist of two parts (clip modules) that are positioned around the cable and pushed together until the parts click into place. The cable feeds are positioned inside the corresponding frame and secured to the frame with the clamping brackets.

To remove the cables, proceed in reverse order. To remove the clip modules from the cable, the holding clips of the clip modules must first be unlatched, then the clip modules must be pulled apart.

2.4.5 Connecting the Cables

Connecting the Cables to the Terminal Board

The terminal board contains the connections for the +24VDC power supply, the GND connector and the switch contact for the solid-state relay (X1, see Figure 16).

It also contains the connections for the cooling elements, fans and temperature monitoring (X2, see Figure 16), the optional error outputs, a protective circuit that protects the sensor from transient interference such as surges or bursts, and a separate ground connection (X3, see Figure 16).




Figure 16: Terminal Board

2.4.6 Pin Allocation

Figure 17 shows the terminal board pin allocation.




Figure 17: Terminal Board Pin Allocation

+24VDC, GND and PE on terminal -X1 are the power supply connections of the TPCC Professional and must be connected according to the diagram shown in Figure 17. Except for the optional error monitoring described in section 2.4.7 the pins on terminal -X2 are connected by PSI Technics. Terminal -X3 is used to ground the TPCC’s aluminum profile. It is connected with the adapter plate mounting screws and does not have to be connected separately. Please note that the labels SSR1, SSR2, and SSR3 refer to the terminal for the solid-state relay.

2.4.7 Error Monitoring (optional)

The TPCC enables integrated error monitoring for the fans and the over-temperature set point.

Potential errors can be read from an transistor output (100mA maximum output) on terminal block X2. In addition, the board has two red indicator LEDs that indicate a fault status. The different switching states are described in the table below.

Table 3: Error Monitoring Switching States

Error	Output 1	Output 2	LED1	LED2
No Fault	Locked	Locked	ON	ON
Fan 1 defective	x	Switched	x	OFF
Fan 2 defective	x	Switched	x	OFF
Fans 1 and 2 defective	x	Switched	x	OFF
Over-temperature	Switched	x	OFF	x

- Error output 1 (terminal X2:11 - X2:10) transmits an over-temperature error.
- Error output 2 (terminal X2:2 - X2:1) transmits a failure of one or both fans.

If these signals should be monitored by a PLC, please use the connection diagram in Figure 17.

2.4.8 Connecting the Solid-state Relay

Connect the solid-state relay (SSR) as shown in the following Figure. The SSR LED indicates the SSR operating state. When the LED lights up the SSR output is connected and the TPCC is operating in cooling mode. When the LED is not illuminated the interior temperature of the TPCC is either below the minimum threshold of 86°F (+30°C) or above the maximum threshold of 122°F (+50°C). The minimum threshold protects the laser distance meter from being cooled down too much; the maximum threshold protects the laser distance meter from overheating.




Figure 18: Connecting the Solid-state Relay

2.4.9 Installing the Solid-state Relay

The solid-state relay should be installed in a freely accessible location within the control cabinet. Use the mounting holes shown in Figure 19 to install the solid-state relay inside the cabinet.




Figure 19: Installing the Solid-state Relay

2.5 Operating the TPCC

The system can be operated once the installation is complete. To guarantee a smooth operation of the TPCC Professional System, the system should be commissioned by authorized service personnel or by specifically trained personnel.



Warning - The TPCC models are only protected to IP55 when mounted horizontally. If the TPCC needs to be mounted in a different position the protection reduces to IP54.



Warning - Prior to operating the TPCC, ensure that all cables are properly connected as shown in the connection diagrams in section 2.4.5. After all of the connections have been checked and are properly connected, the system can be switched on.



Warning - To ensure that the device is protected the screws that secure the upper housing to the lower housing must be tightened with a torque of $1Nm$ using a torque wrench.

2.5.1 SICK DME3000/4000/5000 Distance Meters

When using SICK DME3000/4000/5000 sensors, ensure that the lateral guide plates of the TPCC mount lie flat against the sensor. Mount the sensor according to the instructions in Appendix A, Figures 26 and 25.

2.5.2 SICK DS/DT500 Distance Meters

For mounting SICK DS/DT500 sensors, please refer to the instructions in Appendix A, Figure 27.

2.5.3 SICK DMT-DML Distance Meters

When using a SICK DMT-DML sensor, blanking should be enabled. Blanking is used to ignore objects that are located directly in front of the sensor to avoid measurement errors that can be caused by dirt on the glass pane and to ensure accurate readings even when the glass pane is slightly dirty. When blanking is enabled, the specified sensor data will be collected at a minimum range of 2.0 m. Mount the sensor according to the instructions in Appendix A, Figure 28.

2.5.4 SICK DL100 Pro Distance Meters

When using a SICK DL100 Pro distance meter a 90-degree angle connector must be used to connect the sensor. Mount the sensor according to the instructions in Appendix A, Figure 29.

2.5.5 SICK CLV631/690 Bar Code Scanners

When using SICK CLV631/690 sensors, ensure that the lateral guide plates of the TPCC mount lie flat against the sensor. Mount the sensor according to the instructions in Appendix A, Figures 31 and 32.

2.5.6 SICK LMS400 Distance Meters

When using a SICK LMS400 sensor, ensure that the lateral guide plates of the TPCC mount lie flat against the sensor. Mount the sensor according to the instructions in Appendix A, Figure 33.

2.5.7 SICK WL12G Reflex Sensor

When using a SICK WL12G reflex sensor, the sensor's transmission power must be adjusted using the sensor potentiometer. The sensor has a switching threshold at a measurement signal damping of 8%. The TPCC's glass panel has a transmission percentage of 98% at the corresponding signal wavelength range. Mount the sensor according to the instructions in Appendix A, Figure 34.

2.5.8 SICK Lector[®]620 Professional / ICR620 Bar Code Reader

When using a SICK ICR620 sensor the internal sensor light must be adjusted to prevent it from reflecting on the TPCC's glass panel. It may be necessary to disable the internal sensor light and use an external light instead. Mount the sensor according to the instructions in Appendix A, Figure 35.

2.5.9 SICK DL/DT20

When using a SICK DL/DT20 sensor, ensure that the lateral cooling plates located on the inside are mounted first. After the inner plates have been mounted, mount the outer cooling plates. The outer cooling plates must be lightly pressed against the sensors when mounted on the adapter plate to ensure optimum cooling. Mount the sensor according to the instructions in Appendix A, Figure 36.

2.5.10 SICK Dx1000

While using the sensor Dx1000 care should be taken that this version uses a special front glass panel (art.-no.: 11380) to reach the specified maximal measuring distance of the manufacturers. The utilized panel is optimized for the infrared range of the sensor. For improving the heat dissipation lateral cooling plates are used. These have to be mounted onto the adapter plate before installing the sensor. Mount the sensor according to the instructions in Appendix A, Figure 30.

2.6 Troubleshooting

2.6.1 Troubleshooting the TPCC

If problems occur during the operation of the TPCC Professional System, please check the following and provide PSI Technics support (support@psi-technics.de) with a detailed description of the problem:

1. Ensure that the correct voltage is used
 - Check the power supply unit
 - Ensure that the +24 VDC feed is connected to TPCC terminals X1.1 - X1.2.
2. Check the environmental temperature
 - If the environmental temperature exceeds the maximum threshold, the TPCC's internal temperature is too high and the system will shut down automatically.
 - The system will restart once the temperature is within the specified temperature thresholds.
3. Error Monitoring
 - The optional error monitoring errors can be read from an isolated switching contact on terminal block X2. In addition, the board has two red indicator LEDs that indicate a fault status. The different switching states are described in the table 3 in chapter 2.4.7.
4. Check the plugs
 - Ensure that the plugs X1, X2:1-9 and X2:10-18 are plugged in.
 - Check the correct position of all plugs (No overlapping).
5. Visually check the fans
 - If the optional failure output is not available on the TPCC the proper function of the fans must be checked manually. If one of the fans is no longer working, the system must be shut down.

2.7 Cable Length

2.7.1 Cable Cross-Section $1.5mm^2$




Figure 20: Line Drop, $1.5mm^2$ Cable Cross-Section

PSI Technics recommends a maximum cable length of 82 ft (25 m). When using the maximum cable length the power supply needs to be adjusted as shown in Figure 20.

2.7.2 Cable Cross-Section 2.5mm^2




Figure 21: Line Drop, 2.5mm^2 Cable Cross-Section

PSI Technics recommends a maximum cable length of 82 ft (25 m). When using the maximum cable length the power supply needs to be adjusted as shown in Figure 21.

2.8 Recommended Connectors

The recommended connectors depend on the sensor you are using. All connectors and cables are available from PSI Technics. Connectors can be ordered using the fax order form at the end of this manual or by visiting <http://www.psi-technics.com/EN/Contact.php>.

SICK DME5000

When using a SICK DME5000 Profibus-type distance meter, PSI Technics recommends using a Profibus BUS IN connector (see Figure 22) and a Profibus BUS OUT connector (see Figure 23) the part numbers are listed below.

BUS IN: Part No. KT_1436

BUS OUT: Part No. KT_1437



Figure 22: BUS IN



Figure 23: BUS OUT

SICK DMT/DML

For SICK DMT/DML distance meters with RS232/RS422 interfaces, PSI Technics recommends using the following connector due to the sensor construction:

Part No. KT 1440

The following 45-degree and 90-degree angle connectors are recommended for use with the Profibus version of SICK DMT/DML distance meters:

Part No. KT_1438 (45-degree)

Part No. KT_1436 (90-degree)

SICK DL100 Pro and Dx1000

For SICK DL100 Pro and Dx1000 distance meters the following connectors must be used due to the sensor construction.

Part No. Ethernet connector 10391 (90-degree)

Part No. SSI 10341 (90-degree)

Part No. Power DC 10741 (90-degree)



Figure 24: 90-Degree Ethernet Connector

In addition, an angled cable socket must be used for the 8-pin SSI interface. For the SSI interface the same angled connector can be used as for SICK DMT/DML sensors (Part number KT_1436 (90-degree)). Prefabricated cables in various lengths are available. Adapter cables for replacing

DME3000/4000/5000 sensors with DL100 Pro distance meters are also available from PSI Technics.

SICK Lector[®] 620 Professional / ICR620

For SICK ICR620 sensors cables with straight connectors must be used.



NOTE - All connectors and cables are available from PSI Technics. Connectors can be ordered using the fax order form at the end of this manual or by visiting:

<http://www.psi-technics.com/EN/Contact.php>.

3 Reader Comment Form

**TPCC Technical Documentation - TPCC
(DM, T/DM, CLV, LMS Models)
November 2023 / Version 3.4.8**

We appreciate your comments and suggestions for improving this publication.

Which PSI Technics product do you use?

What are you using the PSI Technics product for?

Please circle a response for each of the statements below:

1 = Strongly agree 2 = Agree 3 = Neutral; 4 = Disagree; 5 = Strongly disagree

The manual is well organized	1	2	3	4	5
I can find the information I need	1	2	3	4	5
The information in the manual is accurate	1	2	3	4	5
The instructions are easy to understand	1	2	3	4	5
The manual contains sufficient examples	1	2	3	4	5
The examples are appropriate and helpful	1	2	3	4	5
The layout and format are attractive and useful	1	2	3	4	5
The illustrations are clear and helpful	1	2	3	4	5

Please answer the following questions:

Which sections do you use the most?

What do you like most about the manual?

What could be improved?

Reader Comment Form

We appreciate your feedback. Your feedback about the supporting documentation helps us to improve it with each revision. Please use one of the following methods to send us your comments or suggestions:

- Email your feedback to support@psi-technics.com
- Fill in the Reader Comment Form and mail it to the address listed on the bottom of the form

If this manual does not include a Reader Comment Form, please send your feedback to the address listed at the beginning of this manual. Please use the following subject line:

Subject: **TPCC/DM, T/DM, CLV and LMS Reader Comment Form**

Please send us your feedback using one of the following methods:

Mail to:	Fax to:	Email to:
PSI Technics	+49 2630 91590 - 99	support@psi-technics.com
Subject: TPCC	Subject: TPCC	Subject: TPCC
An der Steinkaul 6a		
D-56333 Winningen		
Germany		

All comments and suggestions become the property of
PSI Technics.

4 Notes

5 Support

5.1 General

Technical Support

If you have a problem and cannot find the information you need in the product documentation, contact your local PSI Technics office or PSI Technics support. You can also request support:

- Via the PSI Technics website www.psi-technics.com/EN/
- By sending a support request email to:
support@psi-technics.com

5.2 Service and Support

German Headquarters

PSI Technics GmbH
An der Steinkaul 6a
D-56333 Winningen, Germany
Phone +49 2630 91590 - 0
Fax +49 2630 91590 - 99

6 List of Figures, List of Tables and Appendix

Contents

List of Figures	45
List of Tables	47

List of Figures

1	TPCC/DM Front	9
2	TPCC/T/DM Front	9
3	TPCC/CLV & TPCC/LMS Front	10
4	TPCC/CLV & TPCC/LMS Top View	11
5	TPCC Back - All Models	12
6	TPCC Back View - All Models	13
7	TPCC/DM and CLV Models - Side View	13
8	TPCC/T/DM with Tube - Side View	14
9	Mounting the TPCC	18
10	Mounting the TPCC Using Clearance Holes	19
11	New Board	21
12	Old Board	21
13	TPCC Professional Wiring	22
14	Cable Feeds at the Back of the TPCC Housing	24
15	Cable Feeds and Frame Installation Overview	25
16	Terminal Board	26
17	Terminal Board Pin Allocation	27
18	Connecting the Solid-state Relay	29
19	Installing the Solid-state Relay	30
20	Line Drop, 1.5mm ² Cable Cross-Section	35
21	Line Drop, 2.5mm ² Cable Cross-Section	36
22	BUS IN	37
23	BUS OUT	37
24	90-Degree Ethernet Connector	38
25	SICK DME3000 Mounting Instructions	49
26	SICK DME4000/DME5000 Mounting Instructions	50
27	SICK DS/DT500 Mounting Instructions	51

28	SICK DMT/DML Mounting Instructions	52
29	SICK DL100 Pro Mounting Instructions	53
30	SICK Dx1000 Mounting Instructions	54
31	SICK CLV631 Mounting Instructions	55
32	SICK CLV690 Mounting Instructions	56
33	SICK LMS400 Mounting Instructions	57
34	SICK WL12G Mounting Instructions	58
35	SICK Lector [®] 620 Professional / ICR620 Mounting Instructions	59
36	SICK DL/DT20 Mounting Instructions	60

List of Tables

1	Changes and Revisions	IV
2	Overview of Sensors and Corresponding TPCC Models	3
3	Error Monitoring Switching States	28

A

Appendix

Contents

A.1 Appendix - Mounting Instructions (Adapter Plate)	48
---	-----------




Figure 25: SICK DME3000 Mounting Instructions




Figure 31: SICK CLV631 Mounting Instructions




Figure 32: SICK CLV690 Mounting Instructions




Figure 34: SICK WL12G Mounting Instructions




Figure 35: SICK Lector[®]620 Professional / ICR620 Mounting Instructions

Fax Order Form

Fax-Nr. +49 2630 91590 - 99

**US customers: Please send this order form via email to
sales@psi-technics.com**

Billing Address

Company:

Street:

ZIP/City:

Country:

Phone:

Fax:

Customer ID No.

VAT ID No.:

Shipping Address (if different)

Company:

Street:

ZIP/City:

Country:

Shipping Method:

Contact:

Phone:

Fax:

Quantity	Part No.	Description
	G0009_002_0028	TPCC / DME 3000
	G0001_002_0028	TPCC / DME 4000/5000
	G0005_002_0028	TPCC / DS/DT500
	G0007_002_0028	TPCC / DMT/DML
	G0017_002_0028	TPCC / DL100 Pro
	G0021_002_0028	TPCC / CLV 631-0000
	G0026_002_0028	TPCC / CLV 690-0000
	G0013_002_0028	TPCC / LMS 400
	G0029_002_0028	TPCC / WL12G-3B2531
	G0027_002_0028	TPCC / ICR620S-T11503
	10856	TPCC / DL/DT20
	11188	TPCC / Dx1000
	11380	TPCC Window Plane Dx1000
	10465	TPCC Installation Accessory Kit
	10195	TPCC Power Supply Unit 230VAC/24VDC; 20A
	KT_1436	BUS IN Profibus Connector 90-degree DME5000
	KT_1437	BUS OUT Profibus Connector 90-degree DME5000
	KT_1438	Profibus Connector for SICK DMT/DML 45- degree
	KT_1440	RS232/422 Connector for SICK DMT/DML
	10391	Ethernet Connector Dx1000/DL100 Pro (4- pin) 90-degree
	10341	SSI Connector Dx1000/DL100 Pro (8-pin) 90- degree
	10734	Power DC Connector Dx1000/DL100 Pro 90- degree
	KT_0800_000_0001	Solid State Relay
	10767	Fan replacement kit

Date

Stamp/Signature

PSI Technics GmbH
An der Steinkaul 6a
D-56333 Winnigen, Germany

Phone: +49 2630 91590 - 0
Fax +49 2630 91590 - 99
Email: info@psi-technics.com
<http://www.psi-technics.com>

Managing Director:
Karl-Heinz Förderer